

WM with parallel motor mounting



Rodless Models

| Actuator Model | | WM40S | | WM40D | |
|-------------------|---------------------------|--------------------|----------------|--------------------|----------------|
| Lead (mm) | | 5 | | 5 | |
| Torque (Nm) | | 3.0 | | 3.0 | |
| Speed, Max (RPM) | | 3000 | | 3000 | |
| Compatible Motors | | | | | |
| 230V | Low Inertia, w/o Brake | H-4030-P-H00AA | M433-FNNO-1GON | H-4030-P-H00AA | M433-FNNO-1GON |
| | Low Inertia, w/ Brake | H-4030-P-H04AA | M433-FNNB-1GON | H-4030-P-H04AA | M433-FNNB-1GON |
| | Medium Inertia, w/o Brake | F-4030-Q-H00AA | | F-4030-Q-H00AA | |
| | Medium Inertia, w/ Brake | F-4030-Q-H04AA | | F-4030-Q-H04AA | |
| 460V | Low Inertia, w/o Brake | 1326AS-B420G-21 | M433-FNNO-3GON | 1326AS-B420G-21 | M433-FNNO-3GON |
| | Low Inertia, w/ Brake | 1326AS-B420G-21-K4 | M433-FNNB-3GON | 1326AS-B420G-21-K4 | M433-FNNB-3GON |
| | Medium Inertia, w/o Brake | 1326AB-B420E-21 | | 1326AB-B420E-21 | |
| | Medium Inertia, w/ Brake | 1326AB-B420E-21-K4 | | 1326AB-B420E-21-K4 | |

Rodless Models

| Actuator Model | | WM60D | | WM60S | |
|-------------------|---------------------------|--------------------|----------------|--------------------|----------------|
| Lead (mm) | | ALL | | ALL | |
| Torque (Nm) | | 35.0 | | 35.0 | |
| Speed, Max (RPM) | | 3000 | | 3000 | |
| Compatible Motors | | | | | |
| 230V | Low Inertia, w/o Brake | H-6300-Q-H00AA | M476-GNS0-1GON | H-6300-Q-H00AA | M476-GNS0-1GON |
| | Low Inertia, w/ Brake | H-6300-Q-H04AA | M476-GNSB-1GON | H-6300-Q-H04AA | M476-GNSB-1GON |
| | Medium Inertia, w/o Brake | F-6300-R-H00AA | | F-6300-R-H00AA | |
| | Medium Inertia, w/ Brake | F-6300-R-H04AA | | F-6300-R-H04AA | |
| 460V | Low Inertia, w/o Brake | 1326AS-B690E-21 | M476-GNS0-3GON | 1326AS-B690E-21 | M476-GNS0-3GON |
| | Low Inertia, w/ Brake | 1326AS-B690E-21-K6 | M476-GNSB-3GON | 1326AS-B690E-21-K6 | M476-GNSB-3GON |
| | Medium Inertia, w/o Brake | 1326AB-B720E-21 | | 1326AB-B720E-21 | |
| | Medium Inertia, w/ Brake | 1326AB-B720E-21-K7 | | 1326AB-B720E-21-K7 | |

WM with parallel motor mounting



Rodless Models

| Actuator Model | | WM60X | | WM80D | |
|-------------------|---------------------------|--------------------|----------------|--------------------|--------------------|
| Lead (mm) | | 5 | | ALL | |
| Torque (Nm) | | 35.0 | | 55.0 | |
| Speed, Max (RPM) | | 3000 | | 3000 | |
| Compatible Motors | | | | | |
| 230V | Low Inertia, w/o Brake | H-6300-Q-H00AA | M476-GNS0-1G0N | | |
| | Low Inertia, w/ Brake | H-6300-Q-H04AA | M476-GNSB-1G0N | | |
| | Medium Inertia, w/o Brake | F-6300-R-H00AA | | | |
| | Medium Inertia, w/ Brake | F-6300-R-H04AA | | | |
| 460V | Low Inertia, w/o Brake | 1326AS-B690E-21 | M476-GNS0-3G0N | 1326AB-B740E-21 | SJCP-B100X-E-M72AA |
| | Low Inertia, w/ Brake | 1326AS-B690E-21-K6 | M476-GNSB-3G0N | | SJCP-B100X-E-M74AA |
| | Medium Inertia, w/o Brake | 1326AB-B720E-21 | | 1326AB-B740E-21-K7 | SQCP-B100X-E-M72AA |
| | Medium Inertia, w/ Brake | 1326AB-B720E-21-K7 | | | SQCP-B100X-E-M74AA |

Rodless Models

| Actuator Model | | WM80S | | WM120D | |
|-------------------|---------------------------|--------------------|--------------------|--------------------|--|
| Lead (mm) | | ALL | | ALL | |
| Torque (Nm) | | 55.0 | | 80.0 | |
| Speed, Max (RPM) | | 3000 | | 3000 | |
| Compatible Motors | | | | | |
| 460V | Low Inertia, w/o Brake | 1326AB-B740E-21 | SJCP-B100X-E-M72AA | SJCP-B132M-E-M72AA | |
| | Low Inertia, w/ Brake | | SJCP-B100X-E-M74AA | SJCP-B132M-E-M74AA | |
| | Medium Inertia, w/o Brake | 1326AB-B740E-21-K7 | SQCP-B100X-E-M72AA | SQCP-B132M-E-M72AA | |
| | Medium Inertia, w/ Brake | | SQCP-B100X-E-M74AA | SQCP-B132M-E-M74AA | |